Actiontec®

200 Mbps

MegaPlug Ethernet Adapter

Model #: HPE200AV

User Manual

Ver 1.0

Solutions for the Digital Life™

Downloaded from www.Manualslib.com manuals search engine

Table of Contents

1 Introduction 1
- Package Contents 1
- Features 2
- System Requirements 2
- Getting to Know the Ethernet Adapter 3
- Technical Support 4

2 Connecting the MegaPlug Adapter 5
- Connecting the Adapters 5
- Installing the Configuration Utility 6

3 Using the Configuration Utility 9
- Encryption Key 9
- About 10

4 Troubleshooting 11
- Troubleshooting 11
- Frequently Asked Questions 12

5 Setting Up Static IP Address 15
- Windows Vista 15
- Windows XP 20
- Windows 2000 23
- Windows Me 27
- Windows 98 SE 30

6 Setting Up File and Printer Sharing 33
- File Sharing 33
- Printer Sharing 41

A Specifications 43
- General 43
- LED Indicators 44
- Environmental 44

B Glossary 45

Notices 47
- Regulatory Compliance Notices 47
- Modifications 47
- Miscellaneous Legal Notices 48

Limited Warranty 49

Downloaded from www.Manualslib.com manuals search engine

This page left intentionally blank.

Downloaded from www.Manualslib.com manuals search engine

Introduction 1

Thank you for purchasing the Actiontec MegaPlug AV 200 Mpbs Ethernet Adapter. The MegaPlug Ethernet Adapter is one of the easiest ways to enjoy home or small business networking. It operates on the MegaPlug Powerline Specification AV standard, providing fast data transfer speeds over home AC wiring. Since home power lines are the most common medium in households, with multiple outlets in every room, the MegaPlug Ethernet Adapter allows multiple desktop and laptop computers to be networked easily, enabling them to share an Internet connection, printers, files, and games, without any additional wiring. If you want to take your computer networking to the next level, the Actiontec MegaPlug Ethernet Adapter is sure to be one of the keys to your success.

Package Contents

Make sure the following items came in the kit:

- Two Actiontec MegaPlug AV 200 Mbps Ethernet Adapter
- Two Ethernet cables
- Installation CD (includes this manual)
- Quick Start Guide

Downloaded from www.Manualslib.com manuals search engine

Features

- HomePlug Turbo compliant
- 200 Mbps data rate (maximum)
- 128-bit AES encryption
- Two-pronged US power plug (fits ungrounded power outlets)
- Power and Link indicators

System Requirements

- At least one available power outlet
- Standard home power wiring
- Computer with the following:
  - CD-ROM drive
  - IBM compatible running at 200 MHz or better
  - Windows 98SE, Me, 2000, or XP installed
  - 64 MB of RAM
  - Ethernet network adapter
  - TCP/IP installed

Downloaded from www.Manualslib.com manuals search engine

Getting to Know the Ethernet Adapter

This section contains a quick description of the Adapter's external features.

Front Panel

The Adapter's front panel features 3 lights (LEDs):

Power Light

The Power light glows green when sychronized with another device. If the Power light is off, it can still be powered up.

Link Light

The Link light glows green when an Ethernet connection is detected.

Ethernet Light

The Ethernet light flickers when data is being transferred across the Adapter.

Bottom Panel

The Adapter's bottom panel contains one Ethernet port:

Ethernet Port

The Ethernet port is used to connect the Adapter to a computer or gateway/ router via Ethernet cable.

Information Sticker

The information sticker (located beneath the electrical prongs) displays the MAC (Media Access Control) address, device ID, serial number and other information about the Adapter.

Downloaded from www.Manualslib.com manuals search engine

Technical Support

Actiontec Electronics prides itself on making durable, high-quality, high-performance products. If you need assistance, the Actiontec Technical Support Department is available all day every day to provide professional support.

Actiontec Electronics, Inc.

760 N. Mary Avenue
Sunnyvale, CA 94085

Technical Support

Phone: (USA) 1-888-436-0657
E-mail: http://support.actiontec.com/email_support/support_form.php
Internet: www.actiontec.com/support

Downloaded from www.Manualslib.com manuals search engine

Connecting the MegaPlug Adapter 2

To connect the Adapter, it must be connected to a computer, plugged into a standard wall outlet, and the Configuration Utility loaded on the computer.

Connecting the Adapters

To use the Adapters properly, two Adapters should be plugged into electrical outlets, and devices (computers, printers, etc.) connected to them.

Connecting an Adapter to a Computer

1. Get an Adapter and one Ethernet cable.
2. Insert one end of the Ethernet cable into the Ethernet port of the Adapter.
3. Plug the Adapter into a wall outlet.

   ☞ ***Note:*** Do not plug the Adapter into a UPS or power strip with surge protection. The Adapter's network signal may not pass through these devices.

4. Insert the other end of the Ethernet cable into an Ethernet port on the back of a computer.

Connecting an Adapter to a Router/Gateway

1. Get an Adapter and one Ethernet cable.
2. Insert one end of the Ethernet cable into the Ethernet port of the Adapter.
3. Plug the Adapter into a wall outlet.

   ☞ ***Note:*** Do not plug the Adapter into a UPS or power strip with surge protection. The Adapter's network signal may not pass through these devices.

4. Insert the other end of the Ethernet cable into an Ethernet port on a router/gateway connected to a computer.

Downloaded from www.Manualslib.com manuals search engine

5. Insert the other end of the Ethernet cable into an Ethernet port on a router/gateway connected to a computer.

Follow the instructions in the next section, "Installing the Configuration Utility."

Installing the Configuration Utility

After connecting the Adapters, install the Configuration Utility:

1. Insert the Installation CD in the CD-ROM drive of the computer connected to an Adapter.

2. When the "Welcome" screen appears, click **Next**.


Actiontec MegaPlug AV Configuration Utility - InstallShield Wizard
Welcome to the InstallShield for your MegaPlug AV device!
This program will install the MegaPlug AV Configuration Utility on your computer. To continue, click NEXT.
< Back
Next >
Cancel

3. When the "Choose Destination Screen" appears, click **Next**.



Downloaded from www.Manualslib.com manuals search engine

4. When this window appears, click **Finish**.


Actiontec MegaPlug AV Configuration Utility - InstallShield Wizard
Actiontec MegaPlug AV Configuration Utility
The program has been successfully installed.
Don't forget! The User Manual for this MegaPlug AV device is located on the Installation CD-ROM. Make sure and keep this CD in a safe place.
You can find the Configuration Utility by going to Start->Programs->Actiontec MegaPlug AV.
Click FINISH to exit the program.
< Back
Finish
Cancel

5. Repeat for other computers connected to an Adapter.

☞ ***Note***: If using a computer running Windows Vista, you may have to click through a "User Account Control" window to install the program.

The MegaPlug Adapters are now connected and ready to use, and the Configuration Utility is loaded on the computers. Go to chapter 3, "Using the Configuration Utility" for information about changing the default configuration settings of the Adapter.

Downloaded from www.Manualslib.com manuals search engine

This page left intentionally blank.

Downloaded from www.Manualslib.com manuals search engine

Using the Configuration Utility 3

Once the Adapters have been properly connected and installed, the user can further configure the Adapters using the Actiontec MegaPlug AV Configuration Utility. To access the Utility:

1. Click **Start** on the desktop, then **Programs**.
2. From the Programs menu, find "Actiontec MegaPlug AV ," then select **MegaPlug AV Configuration Utility**.

> ☞ ***Note:*** If you are running Windows Vista, instead of selecting "MegaPlug AV Configuration Utility," right-click on it. Then, from the menu that appears, click **Run as Administrator**. A "User Account Control" window appears. Click **Allow**.

The Utility appears on the desktop. See the following sections for more information about the Utility's capabilities.

Encryption Key

Selecting **Encryption Key** from the row of tabs near the top of the Utility's window generates the "Encryption Key" tab.


Actiontec MegaPlug AV Configuration Utility
Encryption Key
About
To protect your Powerline network from outside intruders, it is HIGHLY recommended that you assign a unique Encryption Key that will be used by each of your MegaPlug AV device. To do this, please follow the steps below.
Step 1: Make sure a MegaPlug AV device is connected to this computer. Enter an unique Encryption Key in the box below
Encryption Key
Step 2: Click the button below to change the Encryption Key for this device
Save Key
Repeat Step 1 and 2 for each MegaPlug AV device directly connected this Host
Not Connected
\Device\{3a3b0877-e48c-4a60-a1c

Downloaded from www.Manualslib.com manuals search engine

Enter an encryption key in the "Encryption Key" text box to provide security for your MegaPlug AV network. The key is similar to a password, can be made up of any combination of letters or numbers, from 4 to 8 characters long , and is not case sensitive. Once activated (by clicking **Save Key**), this key must be entered into any device's network configuration to join the MegaPlug AV network.

Important: **All Adapters on the same network must have the same encryption key. If not, they will not be able to connect.**

About

Selecting **About** from the row of tabs near the top of the Utility's window generates the "About" tab.



The About tab displays the MegaPlug Configuration Utility version.

Downloaded from www.Manualslib.com manuals search engine

Troubleshooting 4

This chapter contains a list of problems that may be encountered while using the MegaPlug Ethernet Adapter, and techniques to solve them. Note that these techniques may not be successful in all cases. Also included is a list of frequently asked questions.

Troubleshooting

If the Adapter is showing signs of trouble, before attempting any other troubleshooting procedures, plug the adapter into a working electrical wall socket.

The Power light doesn't light up after I plug the Adapter into a wall outlet.

First, make sure two Adapters are installed and connected. A single installed Adapter will not have any illuminated lights. Then, ensure the wall outlet is working by plugging other electric devices into it. If it is working, plug in the Adapter again, and if the Power light still doesn't illuminate, try plugging it into other wall outlets. If the Adapter is still experiencing this problem, contact technical support.

The Link light doesn't light up on the Adapter.

If the Adapter's Ethernet light is not illuminating, a LAN connection is not being detected.

- Make sure two Adapters are installed and connected. A single installed Adapter will not have any illuminated lights.
- Check the Ethernet adapter on the computer and make sure it is enabled and working properly. Also, make sure the right type of Ethernet cable is being used.

I can't connect to the Internet or any of the other computers on the network.

- Make sure the IP address and TCP/IP protocol are set up properly for all the computers on the network, then try to ping the gateway.

Downloaded from www.Manualslib.com manuals search engine

- Use the Adapter's Configuration Utility to detect all other Adapters on the network. Then, plug the Adapters into adjacent sockets. If the Ethernet lights still don't illuminate, contact technical support.

The Power and Link lights are on, but I can't access the router/gateway from the computer

- Try plugging the Adapters in different power outlets, preferably closer together.
- Make sure all Adapters on the network are using the same security parameters.

Frequently Asked Questions

What's the transfer speed over the Adapter's network?

The Adapter's network transfer speed is 200 Mbps (maximum) over a standard home power line network.

What's the estimated range of the Adapter's network?

Approximately 300 meters (~985 ft.) in wall power lines (one household).

Will the Adapter work in any home?

The Adapter will work in any home with built-in copper wiring. It may not operate in some older homes (pre-1950) with alternate wiring.

Will the Adapter's network signal pass through circuit breakers?

Yes, the Adapter's network signal will pass through circuit breakers. It will not, however, pass through power transformers.

Does the Adapter work with a 100 – 240V AC input ?

Yes.

Downloaded from www.Manualslib.com manuals search engine

Does using the Adapter cause any interference with other home networking devices?

No. The Adapter operates at a different frequency than other power line control devices and can co-exist with technologies such as X-10, CEBus, and LONworks.

Can my neighbor receive the Adapter's network signal?

It is possible for a neighbor to receive the network signal. To prevent this, change the default 128-bit AES security encryption password on the Adapter (see chapter 3).

How do I find out what the current speed and signal strength of the Adapter's network is?

Run the Adapter's Configuration Utility to show current speed and signal strength.

How many Adapters do I need to set up a network?

Two, at minimum.

To set up the Adapter's network correctly, do I have to install the Configuration Utility on each computer on the network?

No, the Configuration Utility is a diagnostic and security tool. Since the Adapter is fully plug-and-play compatible, it needs no software drivers to operate.

How many Adapters can be installed on the same LAN (local area network)?

Actiontec recommends using no more than 16 Adapters on one network.

Downloaded from www.Manualslib.com manuals search engine

This page left intentionally blank.

Downloaded from www.Manualslib.com manuals search engine

Setting Up Static IP Address

5

To communicate with a MegaPlug Ethernet Adapter from a computer on the network, the user may have to switch the IP address settings from DHCP-enabled to static IP, so that the computer and the Adapter are on the same subnet.

To set up static IP on a computer, select the operating system and follow the instructions.

☞ ***Note***: The following procedures are based on the Adapter's factory default IP address. If the Adapter's IP address has been changed, enter the new IP address when instructed to enter an IP address.

Windows Vista

1. From the desktop, click **Start** button in the lower left corner.
2. From the menu that appears, select **Control Panel**.



Downloaded from www.Manualslib.com manuals search engine

3. When the "Control Panel" window appears, double-click **Network and Internet**.



4. The "Network and Internet" window appears. Click **Network and Sharing Center**.


Control Panel ▸ Network and Internet ▸
Search
File Edit View Tools Help
Control Panel Home
System and Maintenance
Security
Network and Internet
Hardware and Sound
Programs
Mobile PC
User Accounts and Family Safety
Appearance and Personalization
Clock, Language, and Region
Ease of Access
Additional Options
Classic View
Recent Tasks
View network status and tasks
View network computers and devices
Connect to a network
Network and Sharing Center
View network status and tasks | Connect to a network | View network computers and devices
Add a device to the network | Set up file sharing
Internet Options
Connect to the Internet | Change your homepage | Manage browser add-ons
Delete browsing history and cookies
Offline Files
Encrypt your offline files | Manage disk space used by your offline files
Windows Firewall
Turn Windows Firewall on or off | Allow a program through Windows Firewall
People Near Me
Sign in or out of People Near Me | Change People Near Me settings
Sync Center
Sync with other computers, mobile devices, or network folders | View sync results | Resolve sync conflicts

Downloaded from www.Manualslib.com manuals search engine

5. The "Network and Sharing Center" screen appears. From the menu on the left, click **Manage network connections**.



6. The "Network Connections" screen appears.. Double-click **Local Area Connection**.



Downloaded from www.Manualslib.com manuals search engine

7. The "Local Area Connection Properties" window appears. In the "This connection uses the following items" list box, double-click **Internet Protocol (TCP/IP)**.



8. The "Internet Protocol (TCP/IP) Properties" window appears.


Internet Protocol Version 4 (TCP/IPv4) Properties
General
Alternate Configuration
You can get IP settings assigned automatically if your network supports this capability. Otherwise, you need to ask your network administrator for the appropriate IP settings.
Obtain an IP address automatically
Use the following IP address:
IP address:
Subnet mask:
Default gateway:
Obtain DNS server address automatically
Use the following DNS server addresses:
Preferred DNS server:
Alternate DNS server:
Advanced...
OK
Cancel

Downloaded from www.Manualslib.com manuals search engine

9. In the **General** tab, make sure the circle next to "Use the following IP Address" is selected. When active, a black dot appears in the circle. If the circle already contains a black dot, leave it alone.

10. Enter the following address in the "IP Address" text box:
    `192.168.1.2`
    Enter the periods in the address by pressing the space bar on the keyboard.

11. Enter the following address in the "Subnet mask" text box:
    `255.255.255.0`
    Enter the periods in the address by pressing the space bar on the keyboard.

12. Click **OK**. The Internet Protocol (TCP/IP) Properties window disappears.

13. In the Local Area Connection Properties window, click **Close**. The Local Area Connection Properties window disappears.

14. Click **Close** in the Local Area Connection Status window. The window disappears.

15. Close the rest of the open windows by clicking on the "**x**" button at the upper right corner of the window.

The computer is now set up with a static IP address.

Downloaded from www.Manualslib.com manuals search engine

Windows XP

1. From the desktop, click **Start** button in the lower left corner.

2. From the menu that appears, select **Control Panel**.



3. When the "Control Panel" window appears, double-click **Network Connections**.



Downloaded from www.Manualslib.com manuals search engine

4. In the "Network Connections" window, double-click **Local Area Connection**. A number may be displayed after the Local Area Connection. If more than one Local Area Connection is listed, locate the one that corresponds to the network card installed in your computer by finding the name of the network card in the "Device Name" column.


Network Connections
File Edit View Favorites Tools Advanced Help
Back Search Folders
Address Network Connections
Go
Name Type Status Device Name Phone # or Host ... Owner
LAN or High-Speed Internet
Local Area Connection 5 LAN or High-Speed Internet Network cable unplugged Realtek RTL8139 Family PCI Fast Ethernet NIC System
Wireless Network Connection 4 LAN or High-Speed Internet Enabled Actiontec PCI 802.11b Wireless Adapter System
Wizard
Network Setup Wizard Wizard
New Connection Wizard Wizard

5. The "Local Area Connection Properties" window appears. Select **General**.

6. In the "This connection uses the following items" list box, double-click **Internet Protocol (TCP/IP)**.


Local Area Connection 5 Properties
General Authentication Advanced
Connect using:
Realtek RTL8139 Family PCI Fast Ethernet NIC
Configure...
This connection uses the following items:
Client for Microsoft Networks
File and Printer Sharing for Microsoft Networks
QoS Packet Scheduler
Internet Protocol (TCP/IP)
Install... Uninstall Properties
Description
Allows your computer to access resources on a Microsoft network.
Show icon in notification area when connected
OK Cancel

Downloaded from www.Manualslib.com manuals search engine

7. The "Internet Protocol (TCP/IP) Properties" window appears.


Internet Protocol (TCP/IP) Properties
General
You can get IP settings assigned automatically if your network supports this capability. Otherwise, you need to ask your network administrator for the appropriate IP settings.
Obtain an IP address automatically
Use the following IP address:
IP address:
192 . 168 . 0 . 2
Subnet mask:
255 . 255 . 255 . 0
Default gateway:
Obtain DNS server address automatically
Use the following DNS server addresses:
Preferred DNS server:
Alternate DNS server:
Advanced...
OK
Cancel

8. In the **General** tab, make sure the circle next to "Use the following IP Address" is selected. When active, a black dot appears in the circle. If the circle already contains a black dot, leave it alone.

9. Enter the following address in the "IP Address" text box:

   `192.168.1.2`

   Enter the periods in the address by pressing the space bar on the keyboard.

10. Enter the following address in the "Subnet mask" text box:

    `255.255.255.0`

    Enter the periods in the address by pressing the space bar on the keyboard.

11. Click **OK**. The Internet Protocol (TCP/IP) Properties window disappears.

12. In the Local Area Connection Properties window, click **Close**. The Local Area Connection Properties window disappears.

13. Click **Close** in the Local Area Connection Status window. The window disappears.

14. Close the Network and Dial-up Connections window by clicking on the "**x**" button at the upper right corner of the window.

The computer is now set up with a static IP address.

Downloaded from www.Manualslib.com manuals search engine

Windows 2000

1. From the desktop, click on the **Start** button in the lower left corner.
2. From the menu that appears, select **Settings**.

3. Another menu appears. Select **Control Panel**.



Downloaded from www.Manualslib.com manuals search engine

4. When the "Control Panel" window appears, double-click **Network and Dial-up Connections**.

5. In the "Network and Dial-up Connections" window, double-click **Local Area Connection**. A number may be displayed after the Local Area Connection. If there is more than one Local Area Connection listed, locate the one that corresponds to the network card installed in the computer by finding the name of the network card in the **Device Name** column.



Downloaded from www.Manualslib.com manuals search engine

6. The "Local Area Connection Status" window appears. Select **General**, then click **Properties**.



7. The "Local Area Connection Properties" window appears. Click **General**.

8. In the "Components checked are used by this connection" list box, double-click **Internet Protocol** (TCP/IP).



Downloaded from www.Manualslib.com manuals search engine

9. The "Internet Protocol (TCP/IP) Properties" window appears.


Internet Protocol (TCP/IP) Properties
General
You can get IP settings assigned automatically if your network supports this capability. Otherwise, you need to ask your network administrator for the appropriate IP settings.
Obtain an IP address automatically
Use the following IP address:
IP address:
192 . 168 . 0 . 2
Subnet mask:
255 . 255 . 255 . 0
Default gateway:
Obtain DNS server address automatically
Use the following DNS server addresses:
Preferred DNS server:
Alternate DNS server:
Advanced...
OK
Cancel

10. In the **General** tab, make sure the circle next to "Obtain an IP Address automatically" is selected. When active, a black dot appears in the circle. If the circle already contains a black dot, leave it alone.

11. Enter the following numbers in the "IP Address" text box:

`192.168.1.2`

Press the space bar on the keyboard to add the periods between the numbers.

12. Enter the following numbers in the "Subnet mask" text box:

`255.255.255.0`

Press the space bar on the keyboard to add the periods between the numbers.

13. Click **OK**. The "Internet Protocol (TCP/IP) Properties" window disappears.

14 In the "Local Area Connection Properties" window, click **OK**. The Local Area Connection Properties window disappears.

15. Click **Close** in the Local Area Connection Status window. The window disappears.

16. Close the Network and Dial-up Connections window by clicking on the "**x**" button at the upper right corner of the window.

The computer is now set up with a static IP address.

Downloaded from www.Manualslib.com manuals search engine

Windows Me

1. From the desktop, click on the **Start** button in the lower left corner.
2. From the menu that appears, select **Settings**.



3. Another menu appears. Select **Control Panel**.



Downloaded from www.Manualslib.com manuals search engine

4. When the "Control Panel" window appears, double-click **Network**.



5. The "Network" window appears. In the "The following network components are installed" list box, locate and double-click **TCP/IP**.



Downloaded from www.Manualslib.com manuals search engine

6. The "TCP/IP Properties" window appears. Click **IP Address**.


TCP/IP Properties
Bindings
Advanced
NetBIOS
DNS Configuration
Gateway
WINS Configuration
IP Address
An IP address can be automatically assigned to this computer. If your network does not automatically assign IP addresses, ask your network administrator for an address, and then type it in the space below.
Obtain an IP address automatically
Specify an IP address:
IP Address:
192.168. 0 . 2
Subnet Mask:
255.255.255. 0
Detect connection to network media
OK
Cancel

7. In the IP Address tab, make sure the circle next to "Specify an IP Address" is selected. When active, a black dot appears in the circle. If the circle already contains a black dot, leave it alone.

8. Enter the following numbers in the "IP Address" text box:

`192.168.1.2`

Do not include the periods; they are automatically entered.

9. Enter the following numbers in the "Subnet mask" text box:

`255.255.255.0`

Do not include the periods; they are automatically entered.

10. Click **OK**. The TCP/IP Properties window disappears.

11. If there is a check in the box next to "Detect connection to network media," click on it to uncheck the box.

12. In the Network window, click **OK**. The Network window disappears.

Downloaded from www.Manualslib.com manuals search engine

13. The "System Settings Change" window appears, asking whether the computer should be restarted. Click **Yes**.


System Settings Change
You must restart your computer before the new settings will take effect.
Do you want to restart your computer now?
Yes
No

The computer restarts. It is now set up with a static IP address.

Windows 98 SE

1. From the desktop, click on the **Start** button in the lower left corner.

2. From the menu that appears, select **Settings**.

3. Another menu appears. Select **Control Panel**.



Downloaded from www.Manualslib.com manuals search engine

4. When the "Control Panel" window appears, double-click **Network**.

5. The "Network" window appears. In the "The following network components are installed" list box, locate and double-click **TCP/IP**.



Downloaded from www.Manualslib.com manuals search engine

6. The "TCP/IP Properties" window appears. Select **IP Address**.



7. In the IP Address tab, make sure the circle next to "Specify an IP Address" is selected. When active, a black dot appears in the circle. If the circle already contains a black dot, leave it alone.

8. Enter the following numbers in the "IP Address" text box:

`192.168.1.2`

Press the space bar on the keyboard to add the periods between the numbers.

9. Enter the following numbers in the "Subnet mask" text box:

`255.255.255.0`

Press the space bar on the keyboard to add the periods between the numbers.

10. Click **OK**. The TCP/IP Properties window disappears.

11. In the Network window, click **OK**. The Network window disappears.

12. The "System Settings Change" window appears, asking whether the computer should be restarted. Click **Yes**.

System Settings Change
You must restart your computer before the new settings will take effect.
Do you want to restart your computer now?
Yes
No

The computer restarts. It is now set up with a static IP address.

Downloaded from www.Manualslib.com manuals search engine

Setting Up File and Printer Sharing

6

This chapter describes how to share files, hard drives, and printers over the MegaPlug network.

File Sharing

To share files, directories, or hard drives on the MegaPlug network, select the operating system running on the computer, then follow the instructions.

Windows XP

After installing and configuring the Adapter, Windows XP automatically enables file sharing. The only item that needs to be altered is workgroup settings. All the computers on the network must have the same workgroup name, but different computer names. To check or change this:

1. Right-click the **My Computer** icon and click **Properties**. The "System Properties" window appears.

2. Select the **Computer Name** tab.



Downloaded from www.Manualslib.com manuals search engine

3. Click **Change**.

4. When the "Computer Name Changes" window appears, enter a new computer name in the "Computer name" text box.



5. Enter a workgroup name in the "Workgroup" text book.

6. Click **OK**.

7. Restart the computer.

Downloaded from www.Manualslib.com manuals search engine

Windows 2000

After installing and configuring the Adapter, Windows 2000 automatically enables file sharing. The only item that needs to be altered is workgroup settings. All the computers on the network must have the same workgroup name, but different computer names. To check or change this:

1. Right-click the **My Computer** icon on your desktop, then select **Properties**.

2. When the "System Properties" window appears, select **Network Identification**.



3. If the **Workgroup** name is already the same as all the other computers on the network, click **OK.** If it is not the same, click **Properties**.

Downloaded from www.Manualslib.com manuals search engine

4. The "Identification Changes" window appears. In the "Computer Name" text box, type a name different than the other computers on the network.



5. In the "Workgroup" text box, enter the network workgroup name. This is the same on each computer on the network.

6. Click **OK**.

7. Click **OK** again.

8. Restart the computer.

Downloaded from www.Manualslib.com manuals search engine

Windows 98, 98SE, and Me

1. Click **Start**, select **Settings**, then **Control Panel**.

2. In the Control Panel window, double-click the **Network** icon. The Network window appears.



3. In the "Configuration" tab, click **Add**. The "Select Network Component Type" window appears.



Downloaded from www.Manualslib.com manuals search engine

4. Select **Service**, then click **Add**. The "Select Network Service" window appears.


Select Network Service
Click the Network Service that you want to install, then click OK. If you have an installation disk for this device, click Have Disk.
Models:
File and printer sharing for Microsoft Networks
File and printer sharing for NetWare Networks
Service for NetWare Directory Services
Have Disk...
OK
Cancel

5. Highlight **File and printer sharing for Microsoft Networks**, then click **OK**.

6. The "File and Print Sharing" window appears. Make sure both options have a check mark in their check boxes. If not, click in the box to activate.

File and Print Sharing
I want to be able to give others access to my files.
I want to be able to allow others to print to my printer(s).
OK
Cancel

Downloaded from www.Manualslib.com manuals search engine

7. Click **OK**. The Network window reappears.

8. In the Network window, select **Identification**. The "Identification" tab appears.



9. In the "Computer Name" text box, type a name different than the other computers on the network.

10. In the "Workgroup" text box, enter the network workgroup name. This is the same on each computer on the network.

11. Enter any description in the "Computer Description" text box. Traditionally, the location name or main user's name is entered.

12. Select **Configuration** to display the Configuration window again.

13. In the "Primary Network Logon" text box, make sure "Client for Microsoft Networks" is entered. If not, click the down arrow and select it from the list.

14. Click **OK**. A "System Settings Change" window appears. Click **Yes**.

Downloaded from www.Manualslib.com manuals search engine

System Settings Change
You must restart your computer before the new settings will take effect.
Do you want to restart your computer now?
Yes
No

15. After your computer restarts, Windows prompts for a user name and password. Enter a user name and password, then write them on a sheet of paper, as they will be needed to access the network in the future.

16. Find a file or hard drive to share, right-click its icon, and select **Sharing**. The "Properties" window appears.

17. In the Properties window, select **Sharing**. The "Sharing" tab appears.



18. Click in the circle next to "Shared As" to share the file or hard drive.

19. Select an **Access Type**:

Read Only - Allows other users on the network to view and read the file or hard drive selected. They will not be able to modify it in any way. You can further restrict their privileges by entering a password in the appropriate text box.

Full - Allows other users on the network to read, modify, move, and delete any information in the shared file or hard drive. You can further restrict their privileges by entering a user name and password.

Downloaded from www.Manualslib.com manuals search engine

Depends on Password - Allows you to set both Read Only and Full access on the shared file or drive. The level of access will depend on the passwords entered in the appropriate field.

20. When finished, click **Apply**, then **OK**.

Printer Sharing

To share a printer connected to the computer, follow these instructions.

☞ ***Note***: These instructions are basically identical for Windows XP, 2000, Me, and 98 SE, with some minor differences.

1. Click **Start**, **Settings**, **Control Panel**.

2. In the "Control Panel" window, double-click on the "Printers" icon.



3. In the "Printers" window, right-click on the icon of the printer to be shared and select **Sharing**.



Downloaded from www.Manualslib.com manuals search engine

4. A "Properties" window appears, with the "Sharing" tab displayed.


HP LaserJet 4L Properties
General
Sharing
Ports
Advanced
Device Settings
You can share this printer with other users on your network. To enable sharing for this printer, click Share this printer.
Do not share this printer
Share this printer
Share name:
HPLaserJet
Drivers
If this printer is shared with users running different versions of Windows, you may want to install additional drivers, so that the users do not have to find the print driver when they connect to the shared printer.
Additional Drivers...
OK
Cancel
Apply

5. Select **Shared As or Share this Printer**. This automatically inserts a default name for the printer share name. You can set a password for the printer at this time if you want to restrict who on the network can use the printer. You can also set the default printer settings by modifying information on the other tabs of this window.

6. Click **OK**, and close all windows.

Downloaded from www.Manualslib.com manuals search engine

Specifications

A

General

Model Number

HPE200AV (MegaPlug AV 200 Mbps Ethernet Adapter)

Standards

HomePlug AV
IEEE 802.3
IEEE 802.3u

Security

128-bit AES link encryption with key management

Frequency Band

2 MHz – 28 MHz

Modulation

OFDM symbol modulation on line synchronozation

Carrier Modulation

QAM, QPSK, BPSK, ROBO carrier modulation

QoS (Quality of Service)

Integrated prioritized random access
Contention-free access
Segment bursting

Other Protocols

TDMA and CSMA/CA channel access scheme
Forward error correction (FEC)
Automatic channel adaptation

Downloaded from www.Manualslib.com manuals search engine

LED Indicators

Power, Link, Ethernet

Environmental

Power

100 - 240v @ 50 - 60 Hz internal

Certifications

FCC part 15 class B
UL
Home Plug certification

Operating Temperature

0º C to 40º C (32ºF to 104ºF)

Storage Temperature

-20ºC to 70ºC (-4ºF to 158ºF)

Operating Humidity

10% to 90% (non-condensing)

Storage Humidity

5% to 90% (non-condensing)

Note: Specifications are subject to change without notice.

Downloaded from www.Manualslib.com manuals search engine

Glossary

B

Client

A desktop or mobile computer connected to a network.

DHCP (Dynamic Host Configuration Protocol)

A protocol designed to automatically assign an IP address to every computer on your network.

DSL (Digital Subscriber Line) Modem

A modem that uses existing phone lines to transmit data at high speeds.

Encryption

A method to allow wireless data transmissions a level of security.

Ethernet Network

A standard wired networking configuration using cables and hubs.

IP (Internet Protocol) Address

A series of four numbers separated by periods identifying a unique Internet computer host.

LAN (Local Area Network)

A group of computers and devices connected together in a relatively small area (such as a house or an office). A home network is considered a LAN.

MAC (Media Access Control) Address

The hardware address of a device connected to a network.

NAT (Network Address Translation)

A method allowing all of the computers on a home network to use one IP address, enabling access to the Internet from any computer on the home network without having to purchase more IP addresses from the ISP.

Router

A central device that manages the data traffic of your network.

Downloaded from www.Manualslib.com manuals search engine

Subnet Mask

A set of four numbers configured like an IP address used to create IP address numbers used only within a particular network.

TCP/IP (Transmission Control Protocol/Internet Protocol)

The standard protocol for data transmission over the Internet.

WAN (Wide Area Network)

A network that connects computers located in separate areas, (i.e., different buildings, cities, countries). The Internet is a WAN.

Downloaded from www.Manualslib.com manuals search engine

Notices

Regulatory Compliance Notices

Class B Equipment

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by implementing one or more of the following measures:

- Reorient or relocate the receiving antenna;
- Increase the separation between the equipment and receiver;
- Connect the equipment to an outlet on a circuit different from that to which the receiver is connected;
- Consult the dealer or an experienced radio or television technician for help.

Modifications

The FCC requires the user to be notified that any changes or modifications made to this device that are not expressly approved by Actiontec Electronics, Inc., may void the user's authority to operate the equipment.

Declaration of conformity for products marked with the FCC logo – United States only.

Downloaded from www.Manualslib.com manuals search engine

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference
2. This device must accept any interference received, including interference that may cause unwanted operation

☞ ***Note***: To comply with FCC RF exposure compliance requirements, the antenna used for this transmitter must be installed to provide a separation distance of at least 8 inches from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter.

For questions regarding your product or the FCC declaration, contact:

Actiontec Electronics, Inc.
760 North Mary Ave.
Sunnyvale, CA 94086
United States
Tel: (408) 752-7700
Fax: (408) 541-9005

Miscellaneous Legal Notices

© 2007 Actiontec Electronics, Inc. Actiontec Installation Buddy, Connection 1-2-3, Solutions for the Digital Life, Actiontec Digital Gear, and the Actiontec logo are trademarks or registered trademarks of Actiontec Electronics, Inc.

All other names are the property of their respective owners.

Downloaded from www.Manualslib.com manuals search engine

Limited Warranty

Hardware: Actiontec Electronics, Inc., warrants to the end user ("Customer") that this hardware product will be free from defects in workmanship and materials, under normal use and service, for twelve (12) months from the date of purchase from Actiontec Electronics or its authorized reseller.

Actiontec Electronics' sole obligation under this express warranty shall be, at Actiontec's option and expense, to repair the defective product or part, deliver to Customer an equivalent product or part to replace the defective item, or if neither of the two foregoing options is reasonably available, Actiontec Electronics may, in its sole discretion, refund to Customer the purchase price paid for the defective product. All products that are replaced will become the property of Actiontec Electronics, Inc. Replacement products may be new or reconditioned. Actiontec Electronics warrants any replaced or repaired product or part for ninety (90) days from shipment, or the remainder of the initial warranty period, whichever is longer.

Software: Actiontec Electronics warrants to Customer that each software program licensed from it will perform in substantial conformance to its program specifications, for a period of ninety (90) days from the date of purchase from Actiontec Electronics or its authorized reseller. Actiontec Electronics warrants the media containing software against failure during the warranty period. The only updates that will be provided are at the sole discretion of Actiontec Electronics and will only be available for download at the Actiontec Web site, www.actiontec.com. Actiontec Electronics' sole obligation under this express warranty shall be, at Actiontec Electronics' option and expense, to refund the purchase price paid by Customer for any defective software product, or to replace any defective media with software which substantially conforms to applicable Actiontec Electronics published specifications. Customer assumes responsibility for the selection of the appropriate applications program and associated reference materials. Actiontec Electronics makes no warranty or representation that its software products will meet Customer's requirements or work in combination with any hardware or applications software products provided by third parties, that the operation of the software products will be uninterrupted or error free, or that all defects in the software products will be corrected. For any third-party products listed in the Actiontec Electronics software product documentation or specifications as being compatible, Actiontec Electronics will make reasonable efforts to provide compatibility, except where the non-compatibility is caused by a "bug" or defect in the third party's product or from use of the software product not in accordance with Actiontec Electronics published specifications or user guide.

Downloaded from www.Manualslib.com manuals search engine

THIS ACTIONTEC ELECTRONICS PRODUCT MAY INCLUDE OR BE BUNDLED WITH THIRD-PARTY SOFTWARE, THE USE OF WHICH IS GOVERNED BY A SEPARATE END-USER LICENSE AGREEMENT.

THIS ACTIONTEC ELECTRONICS WARRANTY DOES NOT APPLY TO SUCH THIRD-PARTY SOFTWARE. FOR THE APPLICABLE WARRANTY, PLEASE REFER TO THE END-USER LICENSE AGREEMENT GOVERNING THE USE OF SUCH SOFTWARE.

Obtaining Warranty Service: Customer may contact Actiontec Electronics Technical Support Center within the applicable warranty period to obtain warranty service authorization. Dated proof of purchase from Actiontec Electronics or its authorized reseller may be required. Products returned to Actiontec Electronics must be pre-authorized by Actiontec Electronics with a Return Merchandise Authorization (RMA) number marked on the outside of the package, and sent prepaid and packaged appropriately for safe shipment, and it is recommended that they be insured or sent by a method that provides for tracking of the package. The repaired or replaced item will be shipped to Customer, at Actiontec Electronics' expense, not later than thirty (30) days after Actiontec Electronics receives the defective product.

Return the product to:
(In the United States)
Actiontec Electronics, Inc.
760 North Mary Avenue
Sunnyvale, CA 94085

Actiontec Electronics shall not be responsible for any software, firmware, information, memory data, or Customer data contained in, stored on, or integrated with any products returned to Actiontec Electronics for repair, whether under warranty or not.

WARRANTIES EXCLUSIVE: IF AN ACTIONTEC ELECTRONICS PRODUCT DOES NOT OPERATE AS WARRANTED ABOVE, CUSTOMER'S SOLE REMEDY FOR BREACH OF THAT WARRANTY SHALL BE REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT ACTIONTEC ELECTRONICS' OPTION. TO THE FULL EXTENT ALLOWED BY LAW, THE FOREGOING WARRANTIES AND REMEDIES ARE EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES, TERMS OR CONDITIONS, EXPRESS OR IMPLIED, EITHER IN FACT OR BY OPERATION OF LAW, STATUTORY OR OTHERWISE, INCLUDING WARRANTIES, TERMS OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, SATISFACTORY QUALITY, CORRESPONDENCE WITH DESCRIPTION, AND NON-INFRINGEMENT, ALL OF WHICH ARE EXPRESSLY DISCLAIMED. ACTIONTEC ELECTRONICS

Downloaded from www.Manualslib.com manuals search engine

NEITHER ASSUMES NOR AUTHORIZES ANY OTHER PERSON TO ASSUME FOR IT ANY OTHER LIABILITY IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE OR USE OF ITS PRODUCTS.

ACTIONTEC ELECTRONICS SHALL NOT BE LIABLE UNDER THIS WARRANTY IF ITS TESTING AND EXAMINATION DISCLOSE THAT THE ALLEGED DEFECT OR MALFUNCTION IN THE PRODUCT DOES NOT EXIST OR WAS CAUSED BY CUSTOMER'S OR ANY THIRD PERSON'S MISUSE, NEGLECT, IMPROPER INSTALLATION OR TESTING, UNAUTHORIZED ATTEMPT TO OPEN, REPAIR OR MODIFY THE PRODUCT, OR ANY OTHER CAUSE BEYOND THE RANGE OF THE INTENDED USE, OR BY ACCIDENT, FIRE, LIGHTNING, OTHER HAZARDS, OR ACTS OF GOD.

LIMITATION OF LIABILITY: TO THE FULL EXTENT ALLOWED BY LAW, ACTIONTEC ELECTRONICS ALSO EXCLUDES FOR ITSELF AND ITS SUPPLIERS ANY LIABILITY, WHETHER BASED IN CONTRACT OR TORT (INCLUDING NEGLIGENCE), FOR INCIDENTAL, CONSEQUENTIAL, INDIRECT, SPECIAL, OR PUNITIVE DAMAGES OF ANY KIND, OR FOR LOSS OF REVENUE OR PROFITS, LOSS OF BUSINESS, LOSS OF INFORMATION OR DATA, OR OTHER FINANCIAL LOSS ARISING OUT OF OR IN CONNECTION WITH THE SALE, INSTALLATION, MAINTENANCE, USE, PERFORMANCE, FAILURE, OR INTERRUPTION OF ITS PRODUCT, EVEN IF ACTIONTEC ELECTRONICS OR ITS AUTHORIZED RESELLER HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, AND LIMITS ITS LIABILITY TO REPAIR, REPLACEMENT, OR REFUND OF THE PURCHASE PRICE PAID, AT ACTIONTEC ELECTRONICS' OPTION. THIS DISCLAIMER OF LIABILITY FOR DAMAGES WILL NOT BE AFFECTED IF ANY REMEDY PROVIDED HEREIN SHALL FAIL OF ITS ESSENTIAL PURPOSE.

Disclaimer: Some countries, states or provinces do not allow the exclusion or limitation of implied warranties or the limitation of incidental or consequential damages for certain products supplied to consumers, or the limitation of liability for personal injury, so the above limitations and exclusions may be limited in their application to you. When the implied warranties are not allowed to be excluded in their entirety, they will be limited to the duration of the applicable written warranty. This warranty gives you specific legal rights which may vary depending on local law.

Dispute Resolution: The customer may contact the Director of Technical Support in the event the Customer is not satisfied with Actiontec Electronics' response to the complaint. In the event that the Customer is still not satisfied with the response of the Director of Technical Support, the Customer is instructed to contact the Director of Marketing. In the event that the Customer is still not satisfied with the response of the Director of Marketing, the Customer is instructed to contact the Chief Financial Officer and/or President.

Downloaded from www.Manualslib.com manuals search engine

Governing Law: This Limited Warranty shall be governed by the laws of the State of California, U.S.A., excluding its conflicts of laws and principles, and excluding the United Nations Convention on Contracts for the International Sale of Goods.

Downloaded from www.Manualslib.com manuals search engine